

# FIBERME

## FW620 WIFI IP Phone

### Portable WIFI Phone

#### FW620

FIBERME FW620 is a portable, elegant Wi-Fi IP-Phone designed for mobile communication applications. With built-in dual-band 2.4GHz & 5GHz Wi-Fi, FW620 can achieve stable and efficient communication in various wireless network environments. Moreover, it integrates Bluetooth 5.0 for pairing with headsets and mobile devices. Installed with a rechargeable 1900mAh battery, FW620 is ready for 9 hours talk time or 200 hours standby time. FW620 is widely used in various wireless scenarios such as enterprises, shopping malls, and hotels, providing users with a high-quality mobile communication experience.



Large Capacity Battery



Roaming



2.4GHz & 5GHz Wi-Fi



PTT Button



Vibration Function



1.8 meter Drop-safe Height



HD Voice Quality



Bluetooth 5

#### General

- Caller ID
- Handset/Hands-free/Headset Mode
- Vibration function
- Standard type-c interface

#### Call Features

- Auto-Answering
- Call out/Answer/Reject
- Call waiting/Switch
- Call forwarding
- Speed Dial
- Intercom
- Anonymous calls
- Restrict outgoing calls
- IP direct dial
- Speed Dial
- Emergency call
- Inquiry (dialing, incoming and outgoing calls)
- Do-Not-Disturb

#### Phone Features

- Network time synchronization
- Multi-language optional
- Blocked List/Allowed List
- Screen saver
- Personalized ringtone settings
- Screen backlight adjustment
- Memorandum
- SMS service
- Voicemail (MWI)
- Menu encryption settings
- Keypad lock/ backlight adjustment

#### Protocols

- RTP/RTCP/SRTP
- STUN
- DHCP
- SNTP
- FTP/TFTP
- HTTP/HTTPS
- TR-069



- Support 16 DSS Keys and one configurable push-to-talk (PTT) button for speed dial
- Up to 9 hours of talk time and up to 200 hours of standby time
- Belt clip
- Desktop charging base
- Standard type-c interface
- Rechargeable Lithium Battery

<b>LCD Screen</b>	2.0" 240 x 320 Color High-Definition LCD Display
<b>Function Keys</b>	<ul style="list-style-type: none"> <li>• 12 Standard phone digits keys</li> <li>• Support 16 DSS Keys</li> <li>• One configurable push-to-talk (PTT) button for speed dial</li> <li>• Navigation Keys</li> <li>• 1 OK key</li> <li>• 2 Volume control keys (Up/Down)</li> <li>• 3 Soft Keys</li> <li>• Phonebook Key</li> <li>• Speaker Key</li> <li>• 1 PTT Key</li> <li>• 1 Power</li> </ul>
<b>SIP Accounts</b>	4 SIP accounts
<b>Network/Connections</b>	Built-in Wi-Fi, support 802.11 a/b/g/n/ac protocol: <ul style="list-style-type: none"> <li>• 2.4GHz IEEE 802.11 b/g/n</li> <li>• 5GHz IEEE 802.11a/n/ac</li> <li>• Encryption: WPA /WPA2-PSK, 802.1X EAP</li> </ul> Built-in Bluetooth 5.0
<b>Languages</b>	English/Chinese/German/French/Italian/Portuguese/Russian/Spanish/Japanese/Korean
<b>Phonebook / Call History</b>	<ul style="list-style-type: none"> <li>• 1000 Records; phonebook search/import/export; XML/LDAP remote phonebook; blacklist</li> <li>• 600 Records; call history: all/missed/dialed/received</li> </ul>
<b>Audio Conferencing</b>	Supports 3-way audio conferencing for easy conference calls
<b>Auto-provision</b>	Auto-Provisioning via FTP/TFTP/HTTP/HTTPS/DHCP OPT66/ SIP PnP/TR-069
<b>Audio Codec</b>	<ul style="list-style-type: none"> <li>• Narrowband Codec: G.711a/u, G.729AB, G.723.1, G.726, iLBC</li> <li>• Wideband Codec: G.722, Opus</li> </ul>
<b>Power Management</b>	<ul style="list-style-type: none"> <li>• DC input: 5V/2A</li> <li>• Charging notification</li> <li>• Full power notification</li> <li>• Low battery notification</li> <li>• After the abnormal shutdown, the device will boot automatically when charging again</li> <li>• Real-time statistics/display of system power</li> </ul>



FIBERME Communications LLC  
1749 Old Meadow Rd., Suite 401  
McLean, VA 22102, USA

[www.fiberme.com](http://www.fiberme.com)  
[sales@fiberme.com](mailto:sales@fiberme.com)

